



The palm grip B 1 is an actuating element for our multi-axis and single-axis controller. It can also be used as an actuating element with hydraulic drives. Push buttons, rocker switches, e.t.c., can also be fitted to suit appropriate requirements. These devices have micro changeover contacts.

The palm grip has a highly flexible cable 4 (8) x 0,25 mm² x 450 mm long.

The mounting piece for the drive rod can be supplied with a tapped hole M 8 or M 10 (standard = M 10).

The palm grip B 1 is made of PA plastic and is black in colour.

Contact complement 2 A 250 V AC 15 / 3 A 24 V DC 13
or 0,5 A 250 V AC 15 / 1,5 A 24 V DC 13

Permissible ambient temperature Operating -40°C to +60°C
Storage -50°C to +80°C

Climate resistance
Damp heat constant DIN IEC 68 part 2-3
Damp heat cyclic DIN IEC 68 part 2-30
Degree of protection front IP 54 IEC 529 DIN 40050

Pos.				Contact-complement	Weight gramm	Type	Price EURO
1		Without built in		KBAD / 22	100	B 1	
2 3 4		Rocker switch top tast-0-tast T-0-T installed Pos. 1 Rocker switch top tast-0-rest T-0-R installed Pos. 1 Rocker switch top rest-0-rest R-0-R installed Pos. 1		KBAD / 18	2 change over contact 2 A 250 V AC 15	120	B 1 W
5		Rocker switch top tast-0-tast T-0-T installed Pos. 1 with push button side installed Pos. 3		KBAD / 29	2 change over contact 2 A 250 V AC 15 1 change over contact 0,5 A 250 V AC 15	130	B 1 WD
6		Rocker switch top tast-0-tast T-0-T installed Pos. 1 with 2 push button side installed Pos. 2+3		KBAD / 67	2 change over contact 2 A 250 V AC 15 2 change over contact 0,5 A 250 V AC 15	140	B 1 W2D
7 8		Push button top with mechanical operation installed Pos. 1 Push button top installed Pos. 1		KBAD / 27 KBAD / 25	1 change over contact 0,5 A 250 V AC 15	120 100	B 1 T B 1 D
9 10		Push button top with 1 push button side installed Pos. 1 Push button top with 2 push button side installed Pos. 2 installed Pos. 2+3		KBAD / 20	2 change over contact 0,5 A 250 V AC 15 3 change over contact 0,5 A 250 V AC 15	120 130	B 1 2D B 1 3D
11 12 13		1 push button side installed Pos. 1 2 push button side installed Pos. 2 3 push button side installed Pos. 3		KBAD / 31	change over contact 0,5 A 250 V AC 15	110 120 130	B 1 D B 1 2D B 1 3D
14		Push button top installed Pos. 1 with Rocker switch side tast-0-tast (protection IP 41) T-0-T installed Pos. 2		KBAD / 75	1 change over contact 0,5 A 250 V AC 15 2 change over contact 0,5A 250V AC 15	120	B 1 DW
15 16 17		Lever switch side 0-tast mechanical operation Lever switch side 0-tast 1 contact Lever switch side 0-tast 2 contacts		KBAD / 586 KBAD / 54 KBAD / 54	change over contact 2 A 250 V AC 15	150 120 130	B 1 K B 1 KD B 1 K2D
21 22		Cable 4 res. 8 x 0,25 mm ² x 450 mm long wired included Pos. 1-17 Additional price per metre cable 4-pole Additional price per metre cable 8-pole					